



Goodman

Part #	HP	Volts	Amps	Type	RPM	Rot.	Body	Frame	Bearing	Cap	Shaft	Cross	Fig
FB-RFB162 ⁻¹	1/50	208/230	0.5	SP	1/3000	CW	8.5"	3.3"	Sleeve	-	-	Roof Top Com: Goodman B29590-00, Fasco 7021-8656	1
FB-RFB140	1/50	115	1.49	SP	1/3400	CCW	5.6"	3.3"	Sleeve	-	-	Goodman-Janitrol GNPS, High Eff. Res: B28330-01, JAIN107NS	2
FB-RFB590	1/50	115	1.22	SP	3000	CW	5.44"	Skel	Ball	-	-	B40590-00, 70023036	3
FB-RFB595	1/50	115	1.22	SP	3000	CW	5.44"	Skel	Ball	-	-	B18590-05	4
FB-RFB859	1/48	115	1.6	SP	1/3000	CW	5.52"	Skel	Ball	-	-	66005, 7002-2307, 7002-2771, 7002-3219, 7058-0229, B1859005, A157, B40590-35, J238-112-11128, J238-1128	5
FB-RFB185 ⁻²	1/35	115	1.46	SP	1/3000	CW	5.8"	Skel	Sleeve	-	-	Goodman-Janitrol GNP Mid Eff. Res: B1859005	6
FB-RFB405 ⁻³	1/33	115	1.5	SP	1/3000	CW	5.9"	Skel	Ball	-	-	66590, 7002-3036, A182, B4059000, J238-112-11195, J238-11195	7
FB-RFB276	1/30	115	1.4	SP	3000	CW	5.44"	Skel	Ball	-	-	0131M00002P	8
FB-RFB501	1/16	115	2.8	SP	3000	CW	5.00"	Skel	Ball	-	-	22307501	9
FB-RFB483	1/8	115	1.8	SP	3200	CW	5.33"	Skel	Ball	-	-	B4833000, B4833000S, A188, 7021-10958, 5KSB46GF0001	10

Grimsby

Part #	HP	Volts	Amps	Type	RPM	Rot.	Body	Frame	Bearing	Cap	Shaft	Cross	Fig
FB-RFB111 ⁻²	1/25	115	1.2	SP	1/3000	CCW	6.0"	3.3"	Sleeve	-	-	SC-OLV-1-2 Mid Efficiency Res: SBC375, CPL1132	11

*Notes:
 1 - Built-in end switch
 2 - Comes with gasket
 3 - Comes with gasket attached